


 Telecommunications Switch  
 Optocoupler/1 Form A Relay

## DESCRIPTION

The TR115-F1 is a dual function circuit designed specifically as a telecommunications switch. It consists an optically isolated solid state relay separated from an optocoupler. The relay portion is composed of an LED on the input, optically coupled to a sensing circuit which drives two source-to-source DMOS transistors. The optocoupler portion of the package consists of two back-to-back LEDs that drive an output phototransistor. The flatpack package is ideal for PCMCIA-type applications.

## FEATURES

- Low input control current
- Function integration
- 20 ohms max on-resistance
- 120mA max continuous load current
- Flatpack package

## APPLICATIONS

- Telecom switching
- PCMCIA cards
- Fax/modem modules
- Set-top boxes
- DAA arrangements
- Hookswitch
- Loop current detect
- Pulse dialing


## OPTIONS/SUFFIXES

- -H High Output Isolation
- -TR Tape and Reel

## MAXIMUM RATINGS

| PARAMETER                     | UNIT | MIN | TYP | MAX |
|-------------------------------|------|-----|-----|-----|
| Storage Temperature           | °C   | -55 |     | 125 |
| Operating Temperature         | °C   | -40 |     | 85  |
| Continuous Input Current      | mA   |     |     | 40  |
| Transient Input Current       | mA   |     |     | 400 |
| Reverse Input Control Voltage | V    | 6   |     |     |
| Output Power Dissipation      | mW   |     |     | 500 |

## SCHEMATIC DIAGRAM



## APPROVALS

- BABT CERTIFICATE #607835:  
BS EN 60950, BS EN 41003, BS EN 60065
- CSA CERTIFICATE #LR111581-1
- UL FILE #E90096


 Telecommunications Switch  
Optocoupler/1 Form A Relay







**ELECTRICAL CHARACTERISTICS - 25°**

| PARAMETER                                    | UNIT    | MIN  | TYP  | MAX | TEST CONDITIONS      |
|--|---------|------|------|-----|----------------------|
| <b>RELAY INPUT SPECIFICATIONS</b>            |         |      |      |     |                      |
| LED Forward Voltage                          | V       |      | 1.2  | 1.5 | If = 10mA            |
| LED Reverse Voltage                          | V       | 6    | 12   |     | Ir = 10uA            |
| Turn-On Current                              | m A     | 5    | 2.5  |     | Io = 120mA           |
| Turn-Off Current                             | m A     |      | 0.5  |     |                      |
| <b>RELAY OUTPUT SPECIFICATIONS</b>           |         |      |      |     |                      |
| Blocking Voltage                             | V       | 400  |      |     | Io = 10uA            |
| Continuous Load Current                      | m A     |      |      | 120 | If = 5mA             |
| On-Resistance                                | Ω       |      | 17   | 20  | Io = 120mA           |
| Leakage Current                              | µ A     |      | 0.7  | 10  | Vo = 400V            |
| Output Capacitance                           | p F     |      | 25   | 50  | Vo = 25V, f = 1.0MHz |
| Offset Voltage                               | m V     |      |      | 0.2 | If = 5mA             |
| Turn-On Time                                 | m s     |      | 2    | 5   | If = 5mA, Io = 120mA |
| Turn-Off Time                                | m s     |      | 0.5  | 1   | If = 5mA, Io = 120mA |
| <b>PHOTOTRANSISTOR INPUT SPECIFICATIONS</b>  |         |      |      |     |                      |
| LED Forward Voltage                          | V       |      | 1.2  | 1.5 | If = 10mA            |
| Turn-On Current                              | m A     | 2    |      |     | Io = 0.5mA           |
| <b>PHOTOTRANSISTOR OUTPUT SPECIFICATIONS</b> |         |      |      |     |                      |
| Breakdown Voltage                            | V       | 60   |      |     | Io = 10uA            |
| Leakage Current                              | n A     |      |      | 500 | Vce = 20V            |
| Collector-Emitter Capacitance                | p F     |      | 6    |     | Vce = 0V, f = 1.0kHz |
| Saturation Voltage                           | V       |      |      | 0.5 | If = 5mA             |
| Current Transfer Ratio                       | %       | 30   | 100  | 800 | If = 2mA, Vce = 5V   |
| <b>COUPLED SPECIFICATIONS</b>                |         |      |      |     |                      |
| Isolation Voltage                            | V       | 2500 |      |     | T = 1 minute         |
| -H Suffix                                    | V       | 3750 |      |     | T = 1 minute         |
| Isolation Resistance                         | G Ω     | 100  |      |     |                      |
| Coupled Capacitance                          | p F     |      |      | 2   |                      |
| Contact Transient Ratio                      | V / µ s | 2000 | 7000 |     | dV = 50V             |



Telecommunications Switch  
Optocoupler/1 Form A Relay

### PERFORMANCE DATA







Telecommunications Switch  
Optocoupler/1 Form A Relay

### MECHANICAL DIMENSIONS


#### **8 PIN FLATPACK PACKAGE**



*END VIEW*



*TOP VIEW*



*BOTTOM VIEW*